



CHANGE TIME / DAY

1. Push and hold **8** until time flashes.
2. For time, push **3** or **9** until correct time shows.
3. For day, push **4** or **10** until correct day shows.
4. To confirm new time and day push **2**.

NOTES FOR HOLIDAY MODE:

- Start time, use steps 1, 2, 15-19 only.
- Radiator water temp 45 all times.
- Room temp 16 all times.
- Hot water continues automatically.

CHANGE HEATING TIMES

1. To start programming push **2** three times. 'MON' and sun symbol flash. Clock symbol, time and temp steady.
2. Push and hold **2** for 5 secs. Everything flashes; clock symbol has 1 beside it.
3. Push **3** or **9** to set first start time, for example 07:00.
4. Push **4** or **10** to set first radiator water temp, for example 70.
5. Push **5** or **11** to set first room temp, for example 22.
6. Push **2** to confirm. Beside clock symbol 1 and 2 show.
7. Push **3** or **9** to set second start time, for example 10:00.
8. Push **4** or **10** to set second radiator water temp, for example 55.
9. Push **5** or **11** to set second room temp, for example 20.
10. Push **2** to confirm. Beside clock symbol 1, 2 and 3 show.
11. Push **3** or **9** to set third start time, for example 16:00.
12. Push **4** or **10** to set third radiator water temp, for example 70.
13. Push **5** or **11** to set third room temp, for example 22.
14. Push **2** to confirm. Beside clock symbol 1,2,3 and 4 show.
15. Push **3** or **9** to set fourth start time, for example 22:00.
16. Push **4** or **10** to set fourth radiator water temp, for example 45.
17. Push **5** or **11** to set fourth room temp, for example 16.
18. Push and hold **2** to confirm. 'Setting' briefly appears and disappears.
19. Push **8** three times to show main screen.

COPY HEATING TIMES FROM ONE DAY TO NEXT.

1. Push **2** twice. 'Mon' and sun symbol flashing.
2. Push and hold **2** and **8** together for 5 secs. 'Setting' briefly appears and disappears. TUE shows.
3. Push and hold **2** and **8** together again each time until 'MON' shows again.
4. Push **8** three times to show main screen.